Contatti REO Italia:
+39 030 279 3883 •
info@reoitalia.it

REOVIB Smart System Mini basic module

IP 00, DIN rail mounting



Unique Selling Point

- Cost-effective phase-angle control systems with vital functionality
- Suitable for 110V- or 240V supplies, ± 10%, 50/60Hz
- Selectable vibrating frequency 50/100Hz / 60/120Hz
- External set-point; potentiometer 10kΩ, 0...+10V, 0(4)...20mA
- Output current max. 6A per module total current 12A
- DIN rail mounting
- Versions available with fill level/overflow control

Description

REOVIB SMART SYSTEM MINI basic module in open design for DIN rail mounting with an output channel of max. 1A. The basic module has a supply for expansion modules, so further output modules can be connected in series up to a total current of 10A.

Technical Data

- Output voltage : 20...100 V / 40...210 V
- Output Current : max. 1 A
- Input voltage switchable : 110/230 V

Last modified: 12.02.2019. All data is provided to the best of our knowledge and awareness and is subject to error and amendment.

Contatti REO Italia:
+39 030 279 3883 •
info@reoitalia.it

REOVIB Smart System Mini basic module

IP 00, DIN rail mounting

Technical data

	SMART Mini Basic module
Mains input	110/230 V switchable
Mains frequency	50/60 Hz +/- 3Hz
Output voltage	20...100 V / 40...210 V
Output current	max. 1A
Vibration frequency	50 / 100 Hz (60 / 120 Hz)
Setpoint value	Potentiometer, 0...10V, 0...20 mA
Ext. Enable	24 V DC, Switch
Umin / Umax	Internal Potentiometer
Soft start	Fixed
Max. Output current from all outputs	10 A
Fill level/overflow control	x
Standards Conformity	CE, RoHS
Protection class	IP00

Dimension drawing







Last modified: 12.02.2019. All data is provided to the best of our knowledge and awareness and is subject to error and amendment.